

Please keep these instructions carefully



**SUITABLE FOR USE WITH LOW ENERGY BULBS**

## **AUTOMATIC DUSK TO TIMED OFF SECURITY LAMP HOLDER**

### **HOW TO FIT**

1. Make sure the light is switched OFF by removing the plug from the socket for a table or standard lamp or switching OFF at the consumer unit for a pendant lamp. Then carefully remove the bulb from the chosen light fitting.
2. Insert the bulb into the socket of the PSL118 and then insert the complete unit into the existing bulb holder.
3. If the bulb is now incorrectly positioned within the shade, remove the shade from the original lamp holder and fit it to the PSL118 being careful not to overtighten the screw fit ring.

### **HOW TO OPERATE**

Use the switch on the side of the PSL118 to select either 3, 6, 9 or 12 hours delay from dusk to switch OFF. Replace the plug or turn ON the supply at the consumer unit and ensure the light switch is turned ON.

The light will turn ON at dusk and stay ON for the number of hours selected and repeat this night after night.

The light switch must remain ON continuously during the time the PSL118 is in use.

### **DO NOT USE**

- The unit in an enclosed fitting such as a flush ceiling luminaire.
- Where a dimmer switch is connected or with fluorescent strip lights, halogen lights or with flicker style candlelight bulbs.
- The unit in bathrooms, shower rooms or open porches. Closed porches are acceptable if the temperature range is within 0 to 40°C and relative humidity is within 20 to 75% (non-condensing).
- Where stability of a table lamp may be affected.
- With emergency exit luminaires.

### **WARNING**

If the shade in use has a closed top and does not allow unrestricted airflow over the unit the maximum wattage with filament/incandescent bulbs must be reduced to 60W. There is no restriction with low energy/compact fluorescent lamps.

Do not exceed the allowable rating in Watts for the shade in use.

This unit takes bayonet fitting Electronic Energy Saving bulbs

**Min: 9W to Max: 20W  
220-240V AC 50Hz**

and normal bayonet fitting filament/incandescent bulbs

**Min: 40W to Max: 100W  
(60W with closed top shade)  
220-240V AC 50Hz**

### **INTERNAL USE ONLY**

Conforms to Directives  
73/23/EEC & 89/336/EEC

**THREE YEAR**

**3**

**GUARANTEE**

Model  
PSL118

Helpline **020 8450 0515**

Call now for a free range brochure on

**020 8452 1112**

For further information contact:

**Timeguard Ltd.**, Victory Park,  
400 Edgware Road, London NW2 6ND  
Or visit our website [www.timeguard.com](http://www.timeguard.com)



5 012483 008768 >